Series

intrinsically safe, II 1 G Ex ia IIB or IIC T6 to T4 Ga, II 1 D Ex ia IIIC T85°C to T135° Da ISO 15218 (CNOMO, size 15) interface, direct operated, pad mounting body, connector size 15

(CFSCIS prefix)

Features and Benefits

• Mini-low consumption valves (0.5 W) for use in potentially explosive atmospheres accord-ing to ATEX-Directive 2014/34/EU

EC type examination certificate no.: INERIS 03 ATEX 0249X IECEx Certificate of Conformity no.: IECEx INE 10.0002X

- · Compliance with the Essential Health and Safety Requirements has been assured by compliance with the International and European Standards IEC and EN: 60079-0 and 60079-11
- The valve's Ex ia protection allows it to be installed in explosive atmospheres up to zone 0 or 20. It can be used in the chemical, oil and pharmaceutical industries, or in processing and packaging plants for flammable products (paints, solvents)
- Compact, monobloc pilot valve with spade plug. Connection according to DIN 43650, form C, 9 4 mm pin spacing
- Version with integrated display and electrical protection. LED visible from 3 sides




Differential pressure 0 - 8 bar [1 bar = 100 kPa]

ISO 15218 (CNOMO E06.36.120N, size 15) Pneumatic base

Connection Subbase Response time 20 ms

Fluids (*)	Temperature range (TS)	Seal materials (∗)
air or inert gas filtered (50 μm), without condensate,	0°C to + 40°C (0.25 W)	NBR (nitrile)
dew point: -20°C	- 10°C to + 40°C (0.5 W)	FPM (fluoroelastomer)



(*) Ensure that compatibility of materials in contact with fluids is verified.

PARA Body

POM, PET, stainless steel and brass Internal parts

Seals NBR, FPM Pneumatic interface seal **TPF**

Other components

Electrical characteristics

Coil insulation class


Connector **Connector specification** Electrical safety **Electrical enclosure protection**

Standard voltages

$\langle \epsilon_x \rangle$	<u>IEC</u>	IECEx
igsquare		8

NC

 $C \in$



PNEUMATIC CNOMO interface


Safety code

🐼 II 1 Ğ Ex ia IIB or IIC T6 to T4 Ga II 1 D Ex ia IIIC T 85°C to T135°C Da

Spade plug (cable Ø 4-6 mm) DIN 43650, 9.4 mm, form C

Moulded IP65 (EN 60529) DC (=) : 12V - 24V (2)

Thermoplastic PET



POWER LEVELS - cold electrical holding values (watt)

1. (1.1.)	power ratings		туріса		ambient			
voltage (U_) (max. ripple	(Pn)(+)	I _(ON) min.	U _(ON)	U (MAX)	U _(OFF)	1	temperature	
10%)	hot/cold =	with LED		recommended		turn off	range (TS)	type (1)
(V)	(W)	(mA)	(V)	(V)	(V)	(mA)	(°C) (1)	
LP1 "24V"	0.25	20	12.2	28	3.3	7	0 to +40/50/60	
LP1 "12V"	0.5	33	11.9	23	3.3	10	-10 to +40/50/60	01
LP1 "24V"	0.5	25	16.4	28	5.7	7	-1010+40/30/00	

(*) Nominal power ratings of standard versions (with LED indicator and electrical protection)

	Safety parameters										
PN	Ui	li	Pi	Ci	Li						
(W)	(V)	(mA)	(W)	(µF)	(μH)						
	In	terface typ	e 1 (versio	n 12 V or 24	4 V) - group IIC						
	28	120	1.6	0	0						
	Interface type 2 (version 12 V or 24 V) - group IIC										
	26	150	1.6	0	0						
0.25/0.5	Interface type 3 (version 12 V or 24 V) - group IIC										
0.23/0.3	20	300	1.6	0	0						
	Inter	face type 4	(version 1	2 V or 24 V	- group IIB & IIIC						
	28	299	1.6	0	0						
	Ir	nterface ty	pe 5 (versi	on 12 V) - g	roup IIC & IIIC						
	17	220	(3.74)	0	0						

Example of use with a Zener barrier installed in a non-hazardous zone: safe area (RS interface) cable explosive area



- (1) Refer to the dimensional drawings.
- (2) Minimum ambient temperature: 0°C (0.25W) / -10°C (0.5W)
- (3) Coil designed for permanent duty within maximum ambient temperature limits. The solenoid valve must be connected to a special certified electrical supply unit installed in a non-dangerous zone. List of safety barrier manufacturers on the following page.

Temperature classification table DC (=)

				• •					
Temperature classification table DC (=)									
Pi				surface tempe	rature				
(Watt)	T6 (8	35°C)		T5 (100°C)	T4 (1	35°C)	T3 (1	35°C)	
	12V	24V	12V	24V	12V	24V	12V	24V	
			Insulatio	on class F (155°C) 100	% E.D. (3)				
1.6	38 (40)	33 (40)	50 (60)	48 (60)	80 (80)	80 (80)	-	-	single solenoid valve
1.6	-	-	44 (55)	40 (45)	79 (80)	75 (80)	-	-	solenoid valve mounted in series
3.74	-	-	-	-	50 (55)	-	80 (80)	-	single solenoid valve
3.74	-	-	-	-	45 (40)	-	80 (80)	-	solenoid valve mounted in series

Specifications

Note: values within parenthesis are related to dust atmospheres

orifice size		flo 3 bar (ANR)		icient v	operating pressure differential (bar)		power coil (power level)	basic catalogue number with impulse /maintained manual operator
					min.	max. (PS)	(W)	=
(mm)	1 → 2	2 → 3	1 → 2	2 → 3		(=)	(=)	
3/2 NC - no	rmally c	losed (W	ith LED a	and prote	ection)			
0.6	4	11	0.04	0.16	0	8	0.25	30215311 IAD
0.6	11	20	0.21	0.44	0	8	0.5	30215106 IAD

When ordering, please specify in addition to the basic catalogue number:

- voltage:

0.5 W: 12 V DC or 24 V DC

Examples: with connector DIN 43650, 9.4 mm: **30215311**IAD 24V DC

with connector DIN 43650, 9.4 mm: **30215106**IAD 12V DC with connector DIN 43650, 9.4 mm: **30215106**IAD 24V DC

Options

• Solenoid valves without LED and electrical protection

Installation

- The solenoid valves can be mounted in any position without affecting operation
- Solenoid valve supplied with mounting screws and mounting pad seal(s)
- Electrical connection between solenoid valve and barrier/interface with cable type A or B according to EN 50039
- Installation on single subbase (3 x M5), brass body, catalogue number 30300001
- Versions with spade-plug connector type ISO 15217/DIN 43650 form C with 8 mm spacing or M12 connection: contact us
- Installation/maintenance instructions are included with each valve

See the list for compatible interfaces and barriers.

This list is for reference only and the user must take into account the cables and the actual supply voltages for the barriers. The operating conditions are calculated as follows:

$$I_{||} (mA) = \frac{0.5 \text{ W: } \textbf{12 V or 24 V with LED}}{(\textbf{V}_{S} - 1.2 - 0.003 (\textbf{R}_{b} + \textbf{R}_{l})] \times 1000}}{(\textbf{R}_{C} + \textbf{R}_{l} + \textbf{R}_{b})} + 3$$

$$\begin{split} \textbf{I}_{| \ \ } & (\text{mA}) = \frac{0.25 \ \text{W: } \textbf{24 V with LED}}{\left(\textbf{V}_{S} - 1.2 - 0.002 \ (\textbf{R}_{b} + \textbf{R}_{| \ }) \ \right] \times 1000}{\left(\textbf{R}_{C} + \textbf{R}_{| \ } + \textbf{R}_{b}\right)} \ \ + 2 \\ & \frac{0.5 \ \text{W or } 0.25 \ \text{W: } \textbf{12 V or } \textbf{24 V without LED}}{\left[\textbf{V}_{S} - 1.2 \ \right] \times 1000} \\ \textbf{I}_{| \ \ } & (\text{mA}) = \frac{\left[\textbf{V}_{S} - 1.2 \ \right] \times 1000}{\left(\textbf{R}_{C} + \textbf{R}_{| \ } + \textbf{R}_{b}\right)} \end{split}$$

This value and the maximum barrier/interface current (if it is non-linear) must be greater than 33 mA (12 V with LED), 25 mA (24 V with LED, 0.5 W) 30mA (12V without LED), 22 mA (24V without LED).

I (mA) Min. supply current of the product

 $\mathbf{R}_{h}(\Omega)$ Max. barrier resistance

T_a (°C) Max. ambient temperature

 $\mathbf{R}_{i}^{"}(\Omega)$ Max. resistance of connecting cables

V_e (V) Min. no-load voltage of barrier/interface

 $\mathbf{R}_{c}(\Omega)$ Max. coil resistance:

12 V with LED =
$$\frac{288 (T_a + 234 + 10)}{254} / 24 \text{ V with LED} = \frac{563 (T_a + 234 + 10)}{254}$$



2

ASCO™ Mini-Solenoid Valves

Compatibles barriers

The 12 V DC and 24 V DC solenoid valves are compatible with the barriers listed in the tables.

Located in safe areas, these barriers allow to feed the intrinsically safe solenoid valves located in explosive areas.

		Interf	ace 1	Interf	ace 2	Interf	ace 3	Interfac	e 4 (IIB)
Supplier	Modules	302 ia IIC 12V LED	302 ia IIC 24V LED	302 ia IIC 12V LED	302 ia IIC 24V LED	302 ia IIC 12V LED	302 ia IIC 24V LED	302 ia IIC 12V LED	302 ia IIC 24V LED
ABB	DO910S	X	X	124 CCD	217 CCD	124 CCD	244 CCD	X	X
Bartec	07-7331-2105/1000	Х						Х	
ŀ	07-7331-2301/1100			Х				Х	
	SB-3722							Х	
Ī	SB-2420							Х	Х
CEAG	SB-3729							Х	Х
	SB-3728	Х	Х					Х	Х
	SB-0728	Х						Х	
EMERSON	DELTA V		Х						Х
GEORGIN	CAPI 2351 E		Х		Х				Х
G.M.	D1040Q - 2			Х				Х	
Internatio nal	D1042Q - 2							Х	Х
IIai	D1043Q - 2	Х		Х				Х	
	815-DO-04	Х	Х					Х	Х
	MTL 3021	Х						Х	
	MTL 3022							Х	Х
	MTL 5021			Х	X			Х	Х
	8215-DO-IS	X		Х				Х	
	MTLx521			Х				Х	
MTL	MTL4521L	X		Х				Х	
	MTL5522							Х	
	4021S	X		Х				Х	
Ī	MTL 722			Х				Х	
Ī	MTL 728	X	Х					Х	Х
Ī	MTL 728P	X	Х					Х	Х
	MTL 779	Х	Х					X	Х

In accordance with the zone classification and the national legislation of each country, apply the certification procedures for the connection of IS-rated products with associated equipment.

All information subject to change without notice. All responsibility for the use of products from other suppliers and the possible modifications of their characteristics is disclaimed.

302

Compatibles barriers

		Interf	face 1	Interf	ace 2	Interf	ace 3	Interfac	ce 4 (IIB)
Supplier	Modules	302 ia IIC 12V LED	302 ia IIC 24V LED	302 ia IIC 12V LED	302 ia IIC 24V LED		ı	1	302 ia IIC 24V LED
	KFD2-SD-Ex1.17					X		×	
	KFD2-SD-Ex1.36							×	×
	KFD2-SD-Ex1.48	×		×				X	
	KFD2-SD-Ex1.48.90A	×		×				×	
	KFD2-SL-Ex1.48	×		×				×	
	KFD2-SL-Ex1.48.90A	×						×	
	KFD2-SL2-Ex1	×	×					×	×
	KFD2-SL2-Ex1.B	×	×					×	×
	KFD2-SL2-Ex1.LK	×	×					×	×
	KFD2-SL2-Ex2	×	×					X	×
	KFD2-SL2-Ex2.B	×	×					×	×
	KFD2-VD-Ex1.1560	×		×		×		×	
	KFD2-VD-Ex1.1835	×	×	×	×			×	×
Pepperl	KFD0-SD2-Ex1.1045	×		×				×	
+ Fuchs	KFD0-SD2-Ex1.1065					×		×	
	LB-2103	×						×	
	LB-2105	×		×				×	
	LB-2112	×	×					×	×
	LB-2112	×	×					×	×
	FB-2203	×						×	
	FB-2203	×						×	
	FB-2205	×		×				×	
	FB-2212	×	×					×	×
	FB 6210	×						×	
	HIC2871	×	×	×	×			×	×
	Z728	×	×					×	×
	Z728.H	×	×					×	×
	Z728.CL	×	×					×	×
	9475/12-04-11			×		×		×	
	9475/12-04-21	×	×					×	×
	9475/12-04-31	×						×	
6	9175/10-16-11s	×						×	
Stahl	9001/01-199-150-101			×		×		×	
	9001/01-280-085-101	×	×					×	×
	9001/01-280-100-101	×	×					×	×
	9001/01-280-110-101	×	×					×	×

In accordance with the zone classification and the national legislation of each country, apply the certification procedures for the connection of IS-rated products with associated equipment.

All information subject to change without notice. All responsibility for the use of products from other suppliers and the possible modifications of their characteristics is disclaimed.

ASCO™ Mini-Solenoid Valves

Compatibles barriers

		Interf	ace 1	Interf	ace 2	Interf	ace 3	Interfac	e 4 (IIB)
Supplier	Modules	302 ia IIC 12V LED	302 ia IIC 24V LED	302 ia IIC 12V LED	302 ia IIC 24V LED	302 ia IIC 12V LED	302 ia IIC 24V LED	302 ia IIC 12V LED	302 ia IIC 24V LED
	MK72-S01-Ex	×		×		×		×	
	MK72-S09-Ex0/24VDC	×		×				×	
	MK72-S10-Ex0/24VDC					×		×	
. .	MC72-41Ex-T/24VDC	×		×		×		×	
Turck	MC72-42Ex-T/24VDC		×		×				×
	MC72-44Ex-T	×		×		×		×	
	MC72-43Ex-T		×		×				×
	IM72-22EX/L	×	×					×	×
	ET200IS double	×	×					×	×
	6ES7132-7FD00-OAB0 II					×		×	
Siemens	6ES7132-7RD10-OAB0 //					×		×	
	6ES7132-7RD20-OAB0			×		×		×	
	6ES7132-7RD20-OAB0 //					×		×	
WAGO	750-535	×	×					×	×

In accordance with the zone classification and the national legislation of each country, apply the certification procedures for the connection of IS-rated products with associated equipment.


All information subject to change without notice. All responsibility for the use of products from other suppliers and the possible modifications of their characteristics is disclaimed.

Dimensions (mm), Weight (kg)





TYPE 01 IEC 335 / DIN 43650 EN/IEC 60079-11/26 II 1 G Ex ia IIC T6 to T4 Ga II 1 D Ex ia IIIC T85°C to T135°C Da




Туре	Weight (1)
01	0.052


- (1) Manual operator location
- 2 Mounting: 2 M3 x 20 screws




Pneumatic base: ISO 15218



Single subbase Brass ф





Orifice (2) can be connected on the left or on the right of the subbase.

Material	Catalog number	Weight (2)	3 Mounting: 2 holes M3, depth 4.5
hrass	30300001	0.034	

⁽²⁾ subbase alone

⁽¹⁾ Including connector.